FCC 电流探头



概　述

FCC公司开发制造的电流探头，具有宽带、高灵敏度、大电流的处理能力，可用频率范围涵盖了基本的电源频率，能满足用户的各种需要。

物理尺寸（mm）								最大初级电流(安培)				
型号	外形图号	A I.D.	B O.D.	C Ht	Zt W[1]	dB W[1]	连接器	DC-60 Hz	400 Hz	RF （CW）	脉冲[2]	频率范围
F-10	1	32	94	64	0.25	-12	N	350	350	100	100	10 Hz-2 MHz
F-10-1	1	32	94	64	0.03	-30	N	100	50	25	500	10 Hz-2 MHz
F-10A	1	67	142	53	0.25	-12	N	350	350	100	100	10 Hz-2 MHz
F-10A-1	1	67	142	53	0.03	-30	N	100	50	25	500	10 Hz-2 MHz
F-12	1	32	94	64	0.32	-10	N	350	350	100	100	10 Hz-3 MHz
F-14	1	32	94	64	0.12	-18	N	400	400	50	500	10 Hz-500kHz
F-14-1	1	32	94	64	0.023	-33	N	400	400	25	500	10 Hz-500kHz
F-14-C	1	32	98	38	0.03	-30	N	100	50	10	100	10 Hz-2 MHz
F-14A	1	67	142	53	0.12	-18.5	N	400	400	50	500	10 Hz-500kHz
F-14A-1	1	67	142	53	0.03	-30.5	N	400	400	25	500	10 Hz-500kHz
F-16	1	32	94	64	4	12	N	400	400	50	300	10 Hz-70 MHz

F-16 -1	1	32	94	64	0.5	-6	N	400	400	3	300	10 Hz-70 MHz
F-16A	1	67	142	53	4	12	N	800	400	50	300	10 Hz-70 MHz
F-16A -1	1	67	142	53	0.5	-6	N	800	400	3	300	10 Hz-70 MHz
F-16M	1	32	98	38	0.5	-6	N	100	100	2	50	100Hz-50 MHz
F-33-1	1	32	71	19	5	14	BNC*	100	100	10	50	10 kHz-250 MHz
F-33-2	1	32	71	19	1	0	BNC*	100	100	2	50	1 kHz-250 MHz
F-33-3	1	32	71	19	4	12	BNC*	100	100	10	50	1 kHz-200 MHz
F-33 -4	?	?	?	?	1	0	BNC*	100	100	2	50	1 kHz-100 MHz
F-33-5	3A	20	51	13	1.3	2.3	SMA	25	25	10	50	10 kHz-140 MHz
F-33-6	1	3	19	19	0.8	-2	SMA	5	5	1	10	1 kHz-200 MHz
F-35	1	32	98	38	1	0	N	350	200	3	100	100 Hz-100 MHz
F-35A	1	32	98	38	1	0	N	350	200	3	100	100 Hz-100 MHz
F-35A-FW	?	32	71	19	1	0	BNC*	350	400	2	100	10 Hz-50 MHz
F-35-1	1	32	98	38	0.15	-16.5	N	350	100	6	500	10 kHz-100 MHz
F-40	1	32	98	38	1	0	N	350	350	100	200	100 Hz-20 MHz
F-40 -5	1	67	153	102	0.1	-20	N	1000	1000	100	5000	10 Hz-50 MHz
F-42	1	32	98	38	6	15.5	N	350	350	50	100	1 kHz-100 MHz
F-43	1	32	98	38	12	4	N	100	100	50	100	100 Hz-100 MHz
F-50	1	32	71	19	9	19	BNC*	300	300	20	50	100 kHz-500 MHz
F-51	1	32	98	38	10	20	N	350	350	50	100	100 kHz-500 MHz

F-52	1	40	117	38	10	20	N	350	350	50	100	100 kHz-500 MHz
F-55	1	32	98	38	1	0	N	350	350	3	100	100 kHz-500 MHz
F-55A	1	32	98	38	0.1	-20	N	350	350	10	100	1 kHz-500 MHz
F-61	1	32	71	19	16	24	BNC*	200	200	20	50	1 MHz-1 GHz
F-62	1	32	71	19	13	22	BNC*	200	200	20	50	10 MHz-1 GHz
F-65	1	32	98	38	1	0	N	350	350	3	100	100 kHz-1 GHz
F-65A	1	32	98	38	0.1	-20	N	350	350	10	100	10 kHz-1 GHz
F-70	1	70	125	38	1	0	N	200	350	3	100	1 kHz-100 MHz
F-71	1	70	125	38	8	18	N	200	200	25	50	10 kHz-500 MHz
F-72	1	67	142	53	5	14	N	350	350	100	100	100 Hz-100 MHz
F-72 -1	1	67	142	53	0.15	-16	N	350	150	12	500	100 Hz-100 MHz
F-72 -2	1	67	142	53	0.005	-46	N	200	70	60	5000	100 Hz-100 MHz
F-73	1	67	142	53	2	6	N	350	350	200	200	10 Hz-30 MHz
F-75	1	70	125	38	1	0	N	350	350	3	100	10 kHz-500 MHz
F-80	1	127	197	41	5	14	N	350	350	100	100	1 kHz-100 MHz
F-80-1	1	127	197	41	1	0	N	350	350	2	100	1 kHz-100 MHz
F-81	1	127	197	41	1	0	N	350	350	100	100	100 Hz-10 MHz
F-2000	1	13	37	17	16	24	SMA	100	100	10	50	10 MHz-3 GHz

物理尺寸										最大初级电流（A）				
型号	外形图号	A	B	C	D	E	Zt W[1]	dB W[1]	连接器	DC-60 Hz	400Hz	RF(CW)	Pulse[2]	频率范围
F-32-9B	4	6	152	46	28	121	3.2	10	SMA	100	100	10	100	100 kHz-300Mhz

苏州泰思特电子科技有限公司

总　　部
地　址：江苏省苏州市科技城峨眉山路99号
电　话：0512-68413700/3800/3900
传　真：0512-68079795
http://www.3ctest.cn　　Email: info@3ctest.cn

北京办事处
地　址：北京海淀区上地信息路甲28号科实大厦D座D 206室
电　话：010-82899984　　010-82899948
传　真：010-82899943　　邮　编:100085

成都办事处
地　址：成都市高新区天益街38号(地铁高新站出口)理想中心3栋1501室
电　话：028-85327800
传　真：028-85311400　　邮　编：6100085

深圳办事处
地　址：深圳市南山区西丽茶光路华文大厦805室
电　话：0755-86626625　　0755-86344313
传　真：0755-26966255　　邮　编：518055

西安办事处
地　址：西安市高新区锦业路（与丈八三路交汇）绿地中央广场维萨瀛海大厦2204室
电　话：029-68985077　　029-68985700
传　真：029-68717677　　邮　编：710077

台湾

台湾利诺科技有限公司
电　话：+886-2-89121185
传　真：+886-2-89121812
地　址：新北市新店区宝桥路235巷130号6F-5
邮　编：23145
http://www.richtec.com.tw
Email：sales@richtec.com.tw

TESTEK 韩国

TESTEK Co.,LTD
Address：601Ho, SungwoonKoa, 141 Hyeonam-ro, Suji-Gu, Yongin-Si, Gyeonggi-Do, 448-808
Tel：070-4099-2072/H.P : 010-6500-6648
Email：woo @testek.co.kr
http://www.testek.co.kr，www.3ctest.co.kr

Chroma QUANTEL 东南亚

Quantel Pte Ltd
Address: 46 Lorong 17 Geylang #05-02
Enterprise Industrial Building
Singapore 388568
Tel: +65 6745 3200
Email: info@quantel-global.com
https://www.quantel-global.com

The EMCShop 北美

The EMC Shop
Address: 7401 Galilee Rd. #160 Roseville, CA 95678
Tel.: 844.423.7435
Email: sales@theemcshop.com
https://www.theemcshop.com

CDIP

Russia Agency:
“CDIP”, llc.
Add.: 121471, Moscow, Ryabinovaya street, house 69, building 5, room. 7
Mr. Sventickiy Andrey
Tel.: +79856003171 / +7(495) 956-20-22
Email: info@cdip.ru / andrey.sventickiy@cdip.ru
www.cdip.ru